




















ZT-3 三相三極零位控制器

圖號	圖號A	圖號B	圖號C	圖號D
參考圖				
尺寸	104x110x155 mm	104x126x170 mm	140x126x170 mm	194x140x200 mm
淨重	1350g	1500g	2255g	4240g
圖號	圖號E	圖號F	圖號G	圖號H
參考圖				
尺寸	133x110x155 mm	133x126x170 mm	175x126x170 mm	235x140x200 mm
淨重	1650g	2000g	2575g	4800g
圖號	圖號I	圖號J	圖號K	圖號L
參考圖				
尺寸	202x110x155 mm	202x126x170 mm	237x140x200 mm	237x110x155 mm
淨重	1880g	2875g	3675g	2200g
圖號	圖號M	圖號N	圖號O	圖號P
參考圖				
尺寸	237x126x170 mm	277x140x200 mm	277x140x200 mm	317x140x200 mm
淨重	3475g	5400g	4235g	5600g
圖號	圖號Q	圖號R	圖號S	
參考圖				
尺寸	358x140x200 mm	468x140x200 mm	648x190x215	
淨重	6160g	9400g	14800g	

訂購資訊：

品名：ZT3 A BBB C D E

例如：ZT3 1 020 2 X A

A→	輸入方式
	1 4-20mA 基本型
	2 0-20mA
	3 1-5V
	4 0-10V
	5 0-5V
	6 2-10V
BBB→	額定負載電流
	020 20 A
	050 50 A
	100 100 A
	160 160 A
	200 200 A
C→	額定負載電壓
	2 220 Vac
	4 440 Vac
D→	特殊功能
	X 基本型
E→	圖號
	A 圖號A
	B 圖號B

### 產品規格

電流	A(av)	$I^2t(A^2s)$	圖號
020	20A	310	B
030	30A	770	B
050	50A	1600	G
070	70A	2700	H
080	80A	3800	H
100	100A	7400	H
120	120A	10600	O
160	160A	18000	R
200	200A	29000	R
300	300A	63000	S